

FEATURE	NI-700	NI-900	NI-2100	ENOVA DVX-2100HD	NI-3100 / NI-3100/256	ENOVA DVX-3150HD	NI-3101-SIG	NI-4100 / NI-4100/256
Integrated NetLinx Master	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Integrated A/V Switcher/Scaler	No	No	No	Yes	No	Yes	No	No
AxLink Interface	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
ICSNet Interface	No	No	Optional	No	Optional	No	No	Yes
10/100 Ethernet	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Digital Input/Output Ports	4	4	4	4	8	8	8	8
RS-232/RS-422/RS-485 Ports	2	1	3	3	7	6	6	7
IR/Serial Output Ports	1	3	4	4	8	8	8	8
Relay Ports	-	-	4	4	8	8	8	8
Expansion Card Slots	No	No	No	No	No	No	No	Yes
IR Receiver Port	Yes	Yes	No	No	No	No	No	No
Programming via Serial Port/Ethernet	Yes/Yes	Yes/Yes	Yes/Yes	USB/Yes	Yes/Yes	Yes/Yes	USB/Yes	Yes/Yes
Built-in Web Server	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Processor Speed	304 MIPS	304 MIPS	404 MIPS	404 MIPS	404 MIPS	404 MIPS	404 MIPS	404 MIPS
On-Board Memory RAM	64 MB	64 MB	64 MB	64 MB	64 MB/256 MB	256 MB	64 MB	64 MB/256 MB
Non-Volatile Memory	512 KB	512 KB	1 MB	1 MB	1 MB	1 MB	1 MB	1 MB
FLASH Memory	32 MB	32 MB	2 GB CF Card	256 MB	2 GB CF Card	256 MB	256 MB	2 GB CF Card
Rack Space	1 RU x 1/3	1 RU x 1/3	2 RU	2 RU	2 RU	3 RU	1 RU	3 RU