



Next Generation Strategy Series II Speaker Systems—The definitive choice for commercial and business applications

In 1991, Atlas Sound shook the commercial sound industry with the introduction of the Strategy Series commercial loudspeaker systems. Strategy Series set the benchmark for "step-up" business and commercial ceiling speaker systems. Since the original Strategy Series introduction many have copied the original Strategy Series concept but few have ever come close to performance of the product that has been the choice of consultants, specifiers and contractors for years. Why? The smooth frequency response, even, wide coverage, sonically pleasing voicing and ease of installation of the Strategy Series have stood the test of time.

The Next Generation

Atlas Sound engineers have taken all feedback received over the years for suggested enhancements to Strategy Series and employed advanced new manufacturing techniques to present Strategy Series II, a series that will "re-set the bar" for commercial audio ceiling speaker systems.

New Models Include:

The **FAP42T** 70.7/100V tuned & ported 4" coaxial ceiling speaker system

The **FAP62T** 70.7/100V tuned & ported 6" coaxial ceiling speaker system

These premium 70.7/100V tuned & ported coaxial ceiling speaker packages will satisfy the needs of owners, architects, contractors, and consultants by delivering true, high fidelity sound reproduction in an attractive and easy-to-install system.

To reduce installation time and simplify ordering and specifying, the **FAP42T** and **FAP62T** packages ship complete with speaker/transformer factory assembled into back can, grille and unique V-rail/C-ring mounting hardware.

Feature Enhancements include

- Front mounted tap selector switch for easy system tuning adjustments
- Unique "trap door" input section allows for through conduit runs with rigid or flex conduit
- 4 Pole detachable "Phoenix" style connector allows easy pre-wiring and is convenient for daisy chaining additional Strategy Series II full range speakers or subwoofers
- "Press fit" grilles blend better into contemporary architecture
- Higher power, enhanced quality 70.7V/100V internal transformers minimize insertion loss and maintain low frequency response while providing increased output for higher SPL applications
- Extended low frequency response from the optimally tuned and ported deep drawn galvanized steel enclosure (285 cubic inches FAP42T, 475 cubic inches FAP62T)

Premium Construction Provides Premium Performance

The high quality construction of the FA series drivers utilized in the **FAP42T** & **FAP62T** will provide familiar performance.

All Strategy Series II drivers feature a weather/UV resistant polypropylene cone with butyl rubber surround coupled with a 19mm PEI tweeter. Crossover components are of the highest quality providing a smooth transition between the driver components insuring even frequency response and coverage.



**C-Ring/V-Rail
Mounting System**

SPECIFICATIONS

MODEL	FAP42T	FAP62T
POWER RATING	25 Watts (Transformer Limited)	50 Watts (Transformer Limited)
70.7V TAPS	1, 2, 4, 8, 16	2, 4, 8, 16, 32
FREQUENCY RESPONSE (±3dB)	75Hz -20kHz	63Hz - 20kHz
SENSITIVITY (1W/1M)	92dB Peak, 88dB Average	91dB Peak, 88dB Average
WOOFER	4" W/ Polypropylene Cone & Butyl Rubber Surround	6" W/ Polypropylene Cone & Butyl Rubber Surround
WOOFER MAGNET WT	10oz (264g)	14oz (398g)
HF DRIVER	Coaxially Mounted PEI Dome Tweeter	Coaxially Mounted PEI Dome Tweeter
DIMENSIONS	10.5"(267mm) Bezel Diameter, 8.97"(228mm) Overall Height	12.5"(318mm) Bezel Diameter, 8.48"(215mm) Overall Height
CUT-OUT DIMENSION	8.9" (226mm)	10.9" (277mm)





Strategy Series® II "Motor Board" Assemblies

Atlas Sound has also addressed retrofit and "division of labor" installations with new "motor board" versions of the Strategy Series II.

Model **FA42T-6MB** is the entire 4" speaker/transformer/selector switch/front plate assembly found in the **FAP42T** assembly. The footprint of the **FA42T-6MB** is identical to a standard FA series 6" speaker component. This footprint allows the motor board to fit into all current Strategy Series 6" enclosures in the exact same manner as a regular 6" FA speaker.

Model **FA62T-8MB** is the entire 6" speaker/transformer/selector switch/front plate assembly found in the **FAP62T** assembly. The footprint of the **FA62T-8MB** is identical to a standard FA series 8" speaker component. This footprint allows the motor board to fit into all current Strategy Series II 8" enclosures in the exact same manner as a regular 8" FA speaker.

FA62T-8MB
Shown in FA97-8 Enclosure, with
FA720-8 Grille and FA81-8 Tile Bridge

SPECIFICATIONS

MODEL	FAP42T-6MB	FAP62T-8MB
SENSITIVITY	88dB Avg/92dB Peak	88dB Avg/91dB Peak
TRANSFORMER	16 Watt @70.7/100V	32 Watt @70.7/100V
TRANSFORMER TAPS	1, 2, 4, 8 & 16 Watts	1, 2, 4, 8 & 32 Watts
MATCHES ENCLOSURE	FA95-6, FA97-6	FA95-8, FA97-8

• Five Year Limited Warranty •



1601 Jack McKay Blvd.
Ennis, TX 75119
AtlasSound.com
Tech Support 800.876.3333

Printed in the USA
Specifications are subject to change without notice.

©Atlas Sound LP. Atlas Sound is a trademark of Atlas Sound LP. All rights reserved.

484210

000302

ATS001153 RevA 3/02